

7 Electrical Parts List

* You can search for updated part codes through CMS web site.

URL : <http://ecms.samsungelectronics.com/>

7-1 Main PCB Parts

Loc. No.	Code No.	Description	Specification	Remarks
-	BN94-00446K	ASSY PCB MAIN-E8	GY15CS	
CIS1	0202-001044	SOLDER-WIRE.	S63S-W3.0,S63S,D3,63Sn/37Pb,-	SNA
CIS2	0202-001222	SOLDER-WIRE FLUX	RS-107,RS60-1.2AA,D1.2,SN60/PB40,-	SNA
CIS3	0204-001095	THINNER	#4520,-,-,-	SNA
CIS4	0204-001677	FLUX	DF-201TVS,MIX,0.820,FLUX 13%,G	SNA
CN102	3701-001219	CONNECTOR-DSUB	15P,3R,FEMALE,ANGLE,AUF	
CN101	3711-004712	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	
-	BN97-00211K	ASSY SMD-E8	GY15CS	SNA
BD101	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
BD104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
BD201	3301-001236	BEAD-SMD	-.60,-,200,-55TO+125C,-,0.7	
BD202	3301-001236	BEAD-SMD	-.60,-,200,-55TO+125C,-,0.7	
BD203	3301-001236	BEAD-SMD	-.60,-,200,-55TO+125C,-,0.7	
C101	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C102	2203-001652	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C103	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C104	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C105	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C106	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C107	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C108	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C109	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C110	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C111	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C113	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C114	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C115	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C116	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C117	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C118	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C119	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C120	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C121	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C122	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C123	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C124	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C125	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C126	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C127	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C128	2203-000440	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C129	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C130	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C131	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C133	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C134	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	

7 Electrical Parts List

Loc. No.	Code No.	Description	Specification	Remarks
C135	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C136	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C137	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C138	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C139	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C140	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C141	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C142	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C143	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C144	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C145	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C146	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C147	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C148	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C149	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C150	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C151	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C152	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C153	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C154	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C155	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C156	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C157	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C158	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C159	2203-000189	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	
C160	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C161	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C162	2203-000626	C-CER,CHIP	0.022NF,5%,50V,COG,TP,1608	
C163	2203-000626	C-CER,CHIP	0.022NF,5%,50V,COG,TP,1608	
C164	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C165	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C169	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C170	2203-000440	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C171	2203-000440	C-CER,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C202	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C203	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C204	2203-000189	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	
C205	2203-000236	C-CER,CHIP	0.1NF,5%,50V,COG,TP,1608	
C206	2203-000357	C-CER,CHIP	0.15NF,5%,50V,COG,TP,1608	
C207	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C208	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C209	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C214	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C215	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C302	2203-000384	C-CER,CHIP	0.015NF,5%,50V,COG,TP,1608	
C303	2203-000626	C-CER,CHIP	0.022NF,5%,50V,COG,TP,1608	
C304	2203-000626	C-CER,CHIP	0.022NF,5%,50V,COG,TP,1608	
C305	2203-000384	C-CER,CHIP	0.015NF,5%,50V,COG,TP,1608	
C309	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C310	2203-000626	C-CER,CHIP	0.022NF,5%,50V,COG,TP,1608	
C311	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
C312	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SNA
C313	2203-000626	C-CER,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C314	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C315	2203-000257	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	
C316	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C407	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C408	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C409	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C410	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C411	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C412	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C413	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C414	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C415	2203-005005	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	
C416	2203-005437	C-CER,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
CIS5	0202-001162	SOLDER-CREAM	RMA-20-21L,S63,-,SN63/PB36.6/AG0.4,FLUX9.5%	
CN103	3711-002127	CONNECTOR-HEADER	BOX,8P,1R,1.25mm,SMD-A,SN	
CN401	3711-003161	CONNECTOR-HEADER	BOX,20P,1R,1.25MM,SMD-A,SN,BEG	
D101	0403-001435	DIODE-ZENER	QZX363C5V6,5.32-5.88,200MW,SOT-363,TP	
D102	0403-001435	DIODE-ZENER	QZX363C5V6,5.32-5.88,200MW,SOT-363,TP	
D201	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D202	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D203	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D204	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D205	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D206	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D207	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D208	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D209	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D210	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D211	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D212	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
IC101	0505-001376	FET-SILICON	FDC6329L,N/P,8V,2.5A,-,0.7W,SC-74	
IC105	1203-002898	IC-POSI.FIXED REG.	G950T45R,T0-252,3P,6.54x6.46mm,PLASTIC,2.475/2.575V,0to+125C,1A,,TP	
IC201	0801-002267	IC-CMOS LOGIC	74LCX14,-,SOIC,14P,150MIL,-,TP,-,-,-,3.6V,-40TO+85C,-,5.5V,-,-,24MA	
IC202	1103-000129	IC-EEPROM	24C02,256x8BIT,SOP,8P,150MIL,1	
IC301	1003-001610	IC-LCD CONTROLLER	RTD2010,PQFP,208P,28x28mm,-,-,TR,PLASTIC,3.3V,0to+70C,-,-,-	
IC302	1103-001023	IC-EEPROM	524C80D81,1028x8Bit,SOP,8P,150MIL,10mS,5V,10%,PLASTIC,0to+70C,110uA,CMOS,TP	
IC303 SOCK	3704-000249	SOCKET-IC	32P,PLCC,SN,1.27mm	
IC401	1205-002412	IC-TRANSMITTER	DTC34LM85A,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,1.4W,0to+70C,TP,LVDS TRANSMITTER	
IC402	1203-002997	IC-VOL. DETECTOR	ELM7529CBA-S,SOT-23,3P,1.5x2.9x1.1mm,PLASTIC,-0.3/+0.3V,200mW,-65to+150C,1.4mA,-	
L102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L103	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L106	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L107	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L201	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L404	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
L406	2703-001334	INDUCTOR-SMD	1.5uH,10%,2012	
MP1.0	BN41-00350A	PCB MAIN	GY15CS,FR4,4,1.0,1.6T,90*110*1.6,LM15P,2	SNA

7 Electrical Parts List

Loc. No.	Code No.	Description	Specification	Remarks
Q101	0501-000342	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	
R101	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R102	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R104	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R107	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R108	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R109	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R110	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R111	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R113	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R114	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R115	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R116	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R117	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R118	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R119	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R120	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R121	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R201	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R202	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R203	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R204	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R205	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R206	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R207	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R208	2703-000310	INDUCTOR-SMD	1.8uH,10%,1608	
R209	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R210	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R211	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R212	2007-000239	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	
R213	2007-000239	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	
R214	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R215	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R216	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R217	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R218	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R219	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R220	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R221	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R222	2007-001164	R-CHIP	75ohm,1%,1/10W,TP,1608	
R224	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R225	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R301	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R302	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R303	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R304	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R305	2007-001167	R-CHIP	75ohm,5%,1/10W,TP,1608	
R306	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
R307	2007-000113	R-CHIP	33ohm,5%,1/10W,TP,1608	
R308	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R309	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description	Specification	Remarks
R310	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R311	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R312	2007-000109	R-CHIP	1Mohm,5%,1/10W,TP,1608	
R313	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R314	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R315	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R316	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R317	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R318	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R319	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R320	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R321	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R322	2007-000078	R-CHIP	1Kohm,5%,1/10W,TP,1608	
R323	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R324	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R325	2007-000090	R-CHIP	10Kohm,5%,1/10W,TP,1608	
R326	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R327	2007-000084	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	
R328	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R329	2007-000074	R-CHIP	100ohm,5%,1/10W,TP,1608	
R411	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R412	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R413	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R414	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R415	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R416	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R417	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R418	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R419	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R420	2007-000071	R-CHIP	22ohm,5%,1/10W,TP,1608	
R421	2007-000070	R-CHIP	0ohm,5%,1/10W,TP,1608	
RA301	2011-001193	R-NET	68ohm,5%,1/16W,L,CHIP,8P,TP	
RA302	2011-001193	R-NET	68ohm,5%,1/16W,L,CHIP,8P,TP	
RA303	2011-001193	R-NET	68ohm,5%,1/16W,L,CHIP,8P,TP	
RA304	2011-001193	R-NET	68ohm,5%,1/16W,L,CHIP,8P,TP	
RA305	2011-001193	R-NET	68ohm,5%,1/16W,L,CHIP,8P,TP	
RA311	2011-001193	R-NET	68ohm,5%,1/16W,L,CHIP,8P,TP	
X301	2801-003326	CRYSTAL-SMD	24MHz,30ppm,28-ABX,16pF,50ohm,	
MICOM	BN97-00335F	ASSY MICOM	GY15CS	
IC303	1107-001456	IC-FLASH MEMORY	Pm39LV010-70JC,128Kx8Bit,PLCC,32P,11.51x14.05mm,70ns,3V,2.7-3.6V,-0to+70C,-,-	
CIS	BN82-00104N	A/S MICOM	GY15CS	SNA

7-2 Others

Loc. No.	Code No.	Description	Specification	Remarks
-	BN90-00432T	ASSY COVER REAR	GY15VSSS/EDC,EDC	SNA
C/R+STD	6003-000337	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(BLK),SWRCH18	SNA
CIS	BN96-00278B	ASSY COVER P-REAR	GOYA,ABS HB BK07	
CIS	BN61-00397A	BRACKET-VESA	GOYA 153S,SECC,T1.0,,,	SNA
CIS	BN63-00561B	COVER-REAR	GOYA,ABS HB BK07	SNA
CIS	BN67-00087C	CAP-GATE	GOYA,ABS HB BK07	SNA
-	BN90-00461J	ASSY STAND	GY15VSSS/EDC,EDC	SNA
CIS	BN96-00281B	ASSY STAND P	GOYA,ABS HB BK07	
CIS	6003-000129	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(YEL),SWRCH18	SNA
STD	6003-000259	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
CIS	6003-000301	SCREW-TAPTITE	BH,+,S,M4,L6,ZPC(YEL),SWRCH18A	SNA
CIS	6003-001185	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
CIS	6003-001188	SCREW-TAPTITE	BH,+,B,M4,L10,YEL,SWRCH18A	SNA
CIS	6502-001088	CABLE CLAMP	DAST-1NB,ID9,T1.5,NYLON66,NTR	SNA
CIS	BN61-00325A	BRACKET-STAND	GOYA15(153V),SECC,T2.0	SNA
CIS	BN61-00341A	BRACKET-BASE	GOYA(153V),SECC,T1.2	SNA
CIS	BN63-00562B	COVER-STAND	GOYA,ABS HB BK07	SNA
CIS	BN63-00564B	COVER-STAND	GOYA,ABS HB BK07	SNA
STD	BN73-00049A	RUBBER-FOOT	MO 15,17,19,CR,11*11,60,T1.5,BLK	SNA
CIS	BN96-00417A	ASSY MISC P-HINGE	GOYA153V,,Zn-2 DIE CASTING	SNA
STD	BN61-00328A	HINGE-BRKT BOTTOM	GOYA15(153V),SK-5 ,T1.5	SNA
STD	BN61-00328B	HINGE-BRKT BOTTOM L	153V,SK-5 ,,T1.5	SNA
STD	BN61-00329A	HINGE-BRKT TOP	GOYA15(153V),Zn-2 DIE CASTING	SNA
-	BN90-00490K	ASSY COVER FRONT	GY15CS	SNA
C/F+C/R	6003-001319	SCREW-TAPTITE	BH,+,B,M3,L10,NI PLT,SWRCH18A,-	SNA
C/F	BN96-00643A	ASSY COVER P-FRONT	GY15CS,ABS HB GR70,SILVER	
CIS	6003-000259	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
CIS	BH68-00035F	LABEL-TC099	MONITOR,GOYA,PE,T0.05,18.8*16.5,CLEAR	SNA
CIS	BN61-00684A	GUIDE-PANEL COM	GY15CS,ABS,HB	SNA
CIS	BN63-00921A	COVER-FRONT	GY15CS,ABS HB GR70,SILVER	SNA
CIS	BN64-00139B	KNOB POWER-FUNCTION	GY15VS,ABS+ PC 5V,BK07	SNA
CIS	BN67-00103A	LENS LED	GY15CS,Acryl	SNA
CIS	BN96-00831A	ASSY BOARD P-FUNCTION	GY15CS,FUNCTION	SNA
-	BN91-00349C	ASSY LCD-E8	GY15CS	SNA
LCD	BN07-00137A	LCD-PANEL	M150X4-L06,G0GH,1024*768,321*245.4*9.7,16.7M,40,0.297*0.297,0-50,3.3V,TN	
-	BN91-00607K	ASSY CHASSIS-E8	GY15CS	
APT+INV	BN44-00102A	ADAPTOR-INVERTER	FSP018-2P101,GY153V,90V/264VAC,50/60HZ,+12V/+3.4V,1.1A/1.2A,20W,AC/DC,0 to +50,-	
CIS	BN96-00741A	ASSY MISC P-D SUB	GY15CS,SPTT T0.5	SNA
CIS	BN63-01030A	SHIELD-D SUB	GY15CS,SPTT,T0.5	SNA
CIS	BN71-00024A	EARTH-PLATE	GH17LS,SUS,T0.15	SNA
-	BN91-00724K	ASSY SHIELD	GY15CSSS/XBM	SNA

Loc. No.	Code No.	Description	Specification	Remarks
CIS	0203-001315	TAPE-CONDUCTOR	DK-K102-30-90,TO.1,W90,L30,GRAY	SNA
CIS	BN39-00244D	CBF SIGNAL	GY15V,15P,15P,20276-N,1830mm,UL20276,BLACK,D-SUB/MALE,W/O CORE,,DET. TYPE	
CIS	BN39-00290A	LEAD CONNECTOR	1504FP,UL1571#30,UL/CSA,20P,140MM,#30,12507HS-20,12507HS-20,BK,1571#30,SJ02-01-1	
CIS	BN63-00563B	COVER-STAND	GOYA,ABS HB BK07	SNA
CIS	BN63-00923A	SHIELD-PANEL CMO	GY15CS,SECC,TO.8	SNA
SH/COV+IP/PCB	6003-000117	SCREW-TAPTITE	BH,+B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/COV+M/PCB	6003-000117	SCREW-TAPTITE	BH,+B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/COV+PAN	6001-000897	SCREW-MACHINE	FH,+M2.5,L4,ZPC(YEL),SWRCH18A,-,-	
SH/D_SUB+SH/PCB	6003-000117	SCREW-TAPTITE	BH,+B,M3,L6,ZPC(YEL),SWRCH18A	SNA
CIS	BN96-00656A	ASSY MISC P-SHIELD-PCB	GY15VS/VT,SPT E TO.3	SNA
CIS	BH68-30003B	LABEL-HIGH VOLTAGE	CKA4217(C),ART,100G,YEL,BLK,W30*L30,CDT-TUBE	SNA
CIS	BN63-00572A	SHIELD-PCB	GOYA15(153V),SPT E,TO.3	SNA
-	BN92-00885W	ASSY P/MATERIAL	GY15CSSS/XBM,SELAMI,UNITED STATES	SNA
P/M	0203-001100	TAPE-OPP MASKING	OPP/W75/CLR,TO.05,W75,L800000,CLR	SNA
P/M	6902-000379	BAG AIR	HDPE,TO.2,L1800,W1000,TRP,,,,PAPER	SNA
CIS	6902-000521	BAG PE	HDPE/NITRON/HDPE,TO.015/TO.5/TO.015,W600,L600,TRP,28 LANGUAGE,2-	SNA
P/M	BH69-00256C	PAD-PACKING-EDGE	MV940,B400,W200,L2030,-,-,YEL,-,-	SNA
P/M	BH69-00457B	PACKING-PAD	GH15,FOAM,T3.0,930,1000	SNA
P/M	BH69-40358A	PACKING-PAD TOP(SKD)	CB-SW4,W815*L1154,200G,CQM5307	SNA
P/M	BH69-40379A	PACKING-WRAP	LDPE,W500*TO.02,-,-	SNA
P/M	BN68-00129A	LABEL SHIPPING	-,LABEL SHIPPING,ART-PAPER,100G,-,WHT,BLACK,-,-,-	SNA
CIS	BN69-00140M	PAD-PALLET COVER	IBM15,SW,800*3540,1295,-,-,-,-,-	SNA
P/M	BN69-00140V	PAD-PALLET COVER	RB15AS,SW4,1200,3530,-,-,-,-,-	SNA
P/M	BN69-00492A	CUSHION-T/B	GY15VS,EPS,,,,,,M50	SNA
P/M	BN69-00617D	PALLET-PACKING	WOODEN,1300,830,120	SNA
-	BN92-00887Q	ASSY BOX	GY15VSSS/XAZ,SEDA,BRAZIL	SNA
CIS	BH68-00329C	LABEL BAR CODE	-,ALL,TC099,DOMESTIC,ART-PAPER 90G,-,WHT,BLACK,-,-,-	SNA
CIS	BH75-10529A	UNIT-HANDLE PACKING	LXA410TLMU,PE,-,WHITE,-	SNA
CIS	BN72-60001A	LEVER-TOP	LSD210TL,PE-LD,WHITE,TFT_LCD	SNA
CIS	BN72-60002A	LEVER-BOTTOM	LSD210TL,PE-LD,WHITE,TFT-LCD	SNA
CIS	BN69-00504K	BOX	S/M153V(GY15VS),SEDA,CB-SW4,YEL,A-1,L416*W394*H151	SNA
-	BN92-00934K	ASSY ACCESSORY	GG15LS	SNA
CIS	BN96-00679K	ASSY ACCESSORY	GG15LS	
CIS	0203-000214	TAPE-OPP MASKING	OPP/W50/CLR,TO.05,W50,L400000,	SNA
CIS	6902-000110	BAG PE	LDPE,TO.05,L356,W240,TRP,28,2,PE MARK	SNA
CIS	BH39-10339X	CBF POWER CORD	DET,SVT,125V/7A,BLK,1830,WALL(ST),MSP-33,MSC-30	
CIS	BH68-00360A	CARD WARRANTY-00	SyncMaster14-1,SELA,MOJO180G,E/S,Latin,297,210	SNA
CIS	BH68-00522A	MANUAL USERS-00	P/CORD SETUP GUIDE,SYNCMaster,EN,W/W,MOJO100G,250,250,00	SNA
CIS	BN96-00594A	ASSY MANUAL P-IB+QSG	Goya,SyncMaster,W/W,21Langs,BN59-355A+BH68-376L	SNA
CIS	BH68-00376L	MANUAL-01	LCDQUICK SETUP GUIDE,SYNCMaster,E/F/S/G/P/L,13LANGS,W/W,MOJO100G,298,420	
CIS	BN59-00355A	S/W DRIVER-USER MANUAL-01	153V,173V,IB/Driver,SyncMaster,W/W,13Langs	SNA
-	BN92-00946Z	ASSY LABEL	GY15CSSS/XBM,SELAMI,UNITED STATES	SNA
CIS	BN68-00518B	LABEL RATING	GY15CS(GH15LS),SS,PE,TO.05,90X45,BLK,POLYESTER,ADC	SNA
-	PA-GY15CSSS/XBM	2	CPT,CLAA150XG09	-

Memo